

March 19, 2022

If wifi won't stay connected, try these, in order:

(for Dell computers but possibly useful for other brands)

- In Control Panel
 - Power Options
 - Change plan settings
 - Change advanced power settings
 - Wireless Adapter Settings
 - Power Saving Mode
- ...choose Maximum Performance
- In Control Panel
 - Device Manager
 - Network adapters
- ...double-click the adapter, choose Power Management, and uncheck "Allow the computer to turn off this device to save power"
- In Services, turn off all Sharebytes services and set WLAN Autoconfig to Automatic.
- In Control Panel, uninstall then re-install the wifi adapter.
- In Control Panel, try disabling all Bluetooth adapters.
- In Control Panel
 - Device Manager
 - Network adapters
- ...double-click the adapter, choose Driver, then try Update Driver and Roll Back Driver.
- Check wifi adapter settings in the BIOS.
- Update the BIOS.